

SP4000

Expandable to 32-Zone Control Panels



Features

- Supports StayD mode
- 4-wire expansion bus
- Expandable to 32 zones
- Expandable to 16 PGMs
- 2 Partitions
- 32 User Codes
- Supports PCS Series
- Supports IP100 Internet Module
- Supports VDMP3 Plug-in voice dialer
- Supports REM3 hand-held remote keypad - require RTX3 V1.31 or higher (SP4000 - One way only)
- Supports iParadox app
- In-field firmware upgradeable via a 307USB
 - - WinLoad for SP5500/SP6000/SP7000
 - - InField Firmware Upgrade Software for SP4000/SP65
- Menu-driven programming for the Installer, Master and Maintenance codes
- Multiple phone numbers: 3 for monitoring station, 5 for personal dialing and 1 for pager reporting (SP65: via PCS200 only - GSM reporting)
- Patented 2 opto coupler dialer circuit - the most reliable dialer in the industry - US Patents 5751803, RE39406 (N/A with the SP65)

- Automatic Daylight Savings Time feature
- Push button software reset (reset to default values and restart)
- Direct connect at 9.6k baud
 - - WinLoad for SP5500/SP6000/SP7000
 - - Babyware for SP4000/SP65
- 256 events buffered
- Fits in 20cm x 25.5cm x 7.6cm (8in x 10in x 3in) and 28cm x 28cm x 7.6cm (11in x 11in x 3in) metal boxes
- EN50131 grade 2

Feature	SP4000	SP5500	SP6000	SP65	SP7000
On-board Zones	4 (8w/ATZ)	5 (10w/ATZ)	8 (16w/ATZ)	9 (18w/ATZ)	16 (32w/ATZ)
On-board PGMs	1	2	2+2*	3	4
Alarm Relay	-	-	1*	-	1
PGM +/- Trigger	-	-	✓	✓ (via BabyWare)	✓
2-Wire Smoke Detector Input	-	-	✓	-	✓
Switching Power Supply	1.1A	1.1A	1.5A	1.1A	1.5A

* = Optional

P ▲ R ▲ D O X™

**Personalized Service,
Innovative Technology Since 1989**